

## Genset

Model	JHY-93GF
Voltage	277/480V
Frequency&Speed	60HZ 1800RPM
Prime Power	93kW/116kVA
Standby Power	102kW/128kVA

## General Engine Data

### Main technical parameters

Number of cylinders	4
Configuration	Vertical, in-line
Aspiration	Turbocharged, air-air intercooled
Combustion system	Direct injection
Compression ratio	16.7:1
Bore	108 mm
Stroke	115 mm
Displacement	4.21 L
Rotation	Counterclockwise (viewed from the flywheel end)
Firing order (viewed from the belt pulley end)	1-3-4-2
Dry weight (without radiator)	450 kg
Wet weight (without radiator)	480 kg

### Overall dimensions

Length (from front end of radiator to rear end of air filter)	1403 mm
Width	740 mm
Height (with radiator and mounting support)	1003 mm

### Centre of gravity (dry engine, with the center of the rear end face of the flywheel shell as the origin)

From the rear end face of the flywheel	387 mm
Height relative to the center of the crankshaft	140 mm

### Fuel consumption

Note: The density of diesel is 0.835 kg/L.

Load condition	1800 r/min	
	g/(kW·h)	L/h
Standby	230	28.9
Prime	235	26.7
75% prime	247	20.0
50% prime	253	14.5

➤ Engine: Yuchai YC4D155-D33

➤ Alternator: Stamford/Leroy Somer  
/Hengsheng

➤ Controller: DeepSea/SmartGen  
/DEIF/ComAp

Centerline deviation relative to the crankshaft center gravity -9 mm

### Moments of rotation inertia

Engine	1.068 kg·m <sup>2</sup>
Flywheel	0.91 kg·m <sup>2</sup>

### Performance rating

Speed droop	≤0.5 %
Steady state speed band	≤0.5 %

### Test conditions

Ambient temperature	25 °C
Atmospheric pressure	100 kPa
Relative humidity	30 %
Max. operating intake resistance	≤5 kPa
Exhaust backpressure limit	≤10 kPa
Fuel temperature (fuel inlet pump)	38±2 °C

Attention: Unless otherwise explicitly specified, all parameter data are measured under standard test condition as above. If the engine is operated under other test conditions rather than the test condition above, it shall be adjusted properly according to the actual environment. Contact the Yuchai Technical Service Department for details.

### Electric system

Type	Negative ground
Charger	
Voltage	28V
Output current	55A
Starter	
Type	Electric start, 1
Voltage	24V
Power	5 kW
Number of teeth of flywheel	130
Number of teeth of starter	11

### Cooling system

Total coolant capacity.....	30L
Engine coolant capacity.....	15L
Radiator coolant capacity.....	12L
Pipeline coolant capacity.....	3L
Engine max. outlet coolant temperature.....	97°C
Thermostat operation temperature	
Initial open.....	(80±2)°C
full open.....	≤90°C
Max. coolant temperature rise:	
-Standby power.....	8°C
-Prime power.....	7°C

### Radiator

Cooling area.....	34.2m <sup>2</sup>
Radiator intercooler dry weight.....	70.5kg
Core material.....	Aluminum
Number of lines.....	/
Density of core.....	13 cooling fins/inch
Width of core.....	680 mm
Height of core.....	600 mm
Min. pressure of pressure cap.....	(50±5)kPa
Coolant resistance limit.....	15 kPa

### Intercooler

Cooling area.....	18.5 m <sup>2</sup>
Core material.....	Aluminum
Number of lines.....	/
Width of core.....	570 mm
Height of core.....	530 mm
Air resistance limit.....	12.8 kPa

### Alternator

Pole No.	4-Pole
Exciter Type	Single bearing, Brushless, Self-excited
Power factor	0.8
Voltage adjust range	≤5%
Insulation Grade	H
Protection Grade	IP23/22
Phase / wire	3 phase 4 wires

### Intake system

Air filter	
Max. intake resistance:	
-Clean air filter .....	2.5 kPa
-Dirty air filter .....	5 kPa
-Air filter type .....	Dry-type, filter cartridge of paper

### Inclination

Transverse inclination (volume of engine oil sump: 11 L) .....	±10°
Longitudinal inclination (volume of engine oil sump: 11 L) .....	±10°

### Fuel system

Injection system.....	High pressure common rail
-----------------------	---------------------------

### Injector

Type.....	Electronically controlled, with multiple jets
-----------	---

### Injector opening pressure

.....	Electronically controlled
-------	---------------------------

### Fuel pump

Drive mode.....	Gear driven
-----------------	-------------

Fuel delivery pump flow @1800 rpm.....	1.2 L/min
--	-----------

Max. fuel inlet temperature limit.....	45 °C
--	-------

Allowed fuel inlet pressure of front end of fuel delivery pump (absolute pressure).....	(35~100) kPa
--	--------------

Maximum fuel return pressure of fuel pump.....	20 kPa
--	--------

### Fuel filter

#### Pre- filter

Rated flow.....	5 L/min
-----------------	---------

Max. original resistance.....	≤ 7 kPa
-------------------------------	---------

Water separation efficiency at the rated flow.....	≥95 %
--	-------

- ❖ NEMAMG1.JIANGHAO, and ANSI standards compliance for temperature rise and motor starting.
- ❖ Sustained short-circuit current of up to 300% of the rated current for up to 10 seconds.
- ❖ Sustained short-circuit current enabling down stream circuit breakers to trip without collapsing the generator field.
- ❖ Self-ventilated and dripproof construction.
- ❖ Superior voltage waveform from two-thirds Pitch windings and skewed stator.
- ❖ Digital solid-state.volts-per-hertz voltage Regulator with +1% no-load to full-load regulation.

## Control Panel



The control module gives digital readouts of:

Generator voltage;  
Output frequency;  
Engine speed;  
Battery voltage;  
Engine hours run.



Dimension:2200\*850\*1200mm

Weight:1000kg



Dimension:3300\*1300\*1800mm

Weight:2100kg

Fuel Tank Capacity:360L

The **control panel** is an Digital Control Module suitable for a wide variety of single, diesel or gas, gen-set applications.

Monitoring an extensive number of engine parameters, the module will display warnings, shutdown and engine status information on the back-lit LCD screen and illuminated LEDs.

### The control module has indicators for failure

information:

Over speed/Low speed,  
Emergency stop  
Low oil pressure;  
High water temperature  
Failure to start  
Battery charger failure

### Automatic shutdown occurs under:

Low engine oil pressure;  
High engine water temperature;  
Over speed/Low speed;  
Failure to start after three attempts.

## Electrical system

- Maintenance-free and anti-explosion battery
- Standard breaker
- ABB breaker (optional)
- ATS (optional)
- Battery charger (optional)
- GMS monitoring (optional)

## Packing

- Wrapping film packaging
- Tray packaging
- plywood box packaging

**Jiangsu Jianghao Generator Co.,Ltd**

**Address:** No.1 Xixu Road, Medical High-tech Zone,  
Taizhou city, Jiangsu, China

**Contact Person:** Anthony Feng

**Email:** [jhf.sale@jhgenerator.com](mailto:jhf.sale@jhgenerator.com)

**WhatsApp:** +86 18652649673

