

JIANGHAO GENERATOR

Genset	
Model	JHY5-120GF
Voltage	230/400V
Frequency&Speed	50HZ 1500RPM
Prime Power	124kW/155kVA
Standby Power	137kW/171kVA

General Engine Data

Main technical parameters

Number of cylinders
ConfigurationVertical, in-line
AspirationTurbocharged, air-air intercooled
Combustion system Direct injection
Compression ratio
Bore
Stroke
Displacement
RotationCounterclockwise (viewed from the flywheel end)
Firing order (viewed from the belt pulley end)1-5-3-6-2-4
Dry weight (without radiator)700 kg
Wet weight (without radiator) 760 kg

Overall dimensions

Length (from	front end	of radiator	to rear	end of air	filter)
--------------	-----------	-------------	---------	------------	---------

1	720 mm
Width	
Height (with radiator and mounting support)1	200 mm

Centre of gravity (dry engine, with the center of the rear end face of the flywheel shell as the origin)

From the rear end face of the flywheel	.412 mm
Height relative to the center of the crankshaft	.142 mm

Fuel consumption

Note: The density of diesel is 0.835 kg/L.

	1500 r/min	
Load condition	g/(kW∙h)	L/h
Standby	214.4	39.0
Prime	210.8	34.9
75% prime	205.4	25.5
50% prime	208.3	17.2

- Engine: Yuchai YC6B205L-D20
- Alternator:Stamford/Leroy Somer /Hengsheng
- Controller:DeepSea/SmartGen
 /DEIF/ComAp

Moments of rotation inertia

Engine	.2.01 kg·m ²
Flywheel	

Performance rating

Speed droop	≤0.5 %	
Steady state speed band	≤0.5 %	

Test conditions

Ambient temperature	
Atmospheric pressure	100 kPa
Relative humidity	
Max. operating intake resistance	
Exhaust backpressure limit	≤10 kPa
Fuel temperature (fuel inlet pump)	

Attention: Unless otherwise explicitly specified, all parameter data are measured under standard test condition as above. If the engine is operated under other test conditions rather than the test condition above, it shall be adjusted properly according to the actual environment. Contact the Yuchai Technical Service Department for details.

Electric system

TypeNegative ground
Charger
/oltage
Dutput current
Starter
TypeElectric start, 1
/oltage
Power6kW/5.5kW
Number of teeth of flywheel
Number of teeth of starter11



Cooling system

Total coolant capacity	
Engine coolant capacity	12 L
Radiator coolant capacity	
Pipeline coolant capacity	3L
Engine max. outlet coolant temperature	
Thermostat operation temperature	
Initial open	(70±2)℃
full open	
Max. coolant temperature rise:	
-Standby power	8°C
-Prime power	
Radiator	
Cooling area	
Dry weight	
Core material	Aluminum
Length of core	
Width of core	
Height of core	
Min. pressure of pressure cap	(90±5)kPa
Coolant resistance limit	15 kPa
Intercooler	
Cooling area	
Core material	
Length of core	
Width of core	
Height of core	
Air resistance limit	

Intake system

Air filter

Max. intake resistance:	
-Clean air filter	3. <mark>5</mark> kPa
-Dirty air filler	<mark>5 k</mark> Pa
-Warning of intake resistance	6.2 kPa
-Air filter type Dry-type, filter can	tridge of paper
Inclination	
Transverse inclination/longitudinal inclinatio engine oil sump: 15 L)	
Fuel system	
Injection systemMechanical pump+elect	ronic governor
Injector	
TypeP-typ	e, mechanical
Injector opening pressure	(25~26) MPa
Fuel pump	
Drive mode	Gear driven
Fuel delivery pump flow @1,500 rpm	3 L/min
Max. fuel inlet temperature limit	57 °C
Allowed fuel inlet pressure of front end of fuel (absolute pressure)	
Maximum fuel return pressure of fuel pump	
Fuel filter	
Rated flow.	1.2 L <i>l</i> min
Max. original resistance	
Water separation efficiency at the rated flow	
Filter efficiency:	
The chockey.	

Alternator

4-Pole
Single bearing, Brushless, Self-excited
0.8
≦5%
Н
IP23/22
3 phase 4 wires

- ♦ NEMAMG1.JIANGHAO, and ANSI standards compliance for temperature rise and motor starting.
- \diamond Sustained short-circuit current of up to 300% of the rated current for up to 10 seconds.
- Sustained short-circuit current enabling down stream circuit breakers to trip without collapsing the generator field.
- ♦ Self-ventilated and dripproof construction.
- ♦ Superior voltage waveform from two-thirds Pitch windings and skewed stator.
- ♦ Digital solid-state.volts-per-hertz voltage Regulator with +1% no-load to full-load regulation.



Control Panel





The control module gives digital readouts of: Generator voltage; Output frequency; Engine speed; Battery voltage;



Dimension:2500*950*1420mm Weight:1480kg



Dimension:3600*1600*1900mm Weight:3280kg Fuel Tank Capacity:550L The **control panel** is an Digital Control Module suitable for a wide variety of single, diesel or gas, gen-set applications.

Monitoring an extensive number of engine parameters, the module will display warnings, shutdown and engine status information on the back-lit LCD screen and illuminated LEDs.

The control module has indicators for failure information:

Over speed/Low speed, Emergency stop Low oil pressure; High water temperature Failure to start Battery charger failure

Automatic shutdown occurs under:

Low engine oil pressure; High engine water temperature; Over speed/Low speed; Failure to start after three attempts.

Electrical system

- Maintenance-free and anti-explosion battery
- Standard breaker
- ABB breaker (optional)
- ATS (optional)
- Battery charger (optional)
- GMS monitoring (optional)

Packing

- Wrapping film packaging
- Tray packaging
- plywood box packaging

Jiangsu Jianghao Generator Co.,Ltd

Address: No.1 Xixu Road, Medical High-tech Zone, Taizhou city, Jiangsu, China

Contact Person: Anthony Feng Email: <u>jhfsale@jhgenerator.com</u> WhatsAPP: +86 18652649673

